



BT-PG 3100/1 **Power Generator**

Art.-No. 41.524.60

This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its continuous power supply of 2,600 watts provides sufficient power for many applications. The large 15-litre tank ensures continuous operation for 11 hours at 2/3 load. The power generator is powered by a highquality 4-stroke engine and is equipped with an overload switch.

BLUE

Features

- Large 15 I tank for continuous power (1)
- Convenient fuel gauge (2)
- 2 x 230 V socket for simple current drain (3)
- Overload switch for equipment reliability (4)
- Practical voltmeter (6)
- Powerful 4-stroke drive motor (7)
- Linkage to start the motor (8)
- Oil deficiency safety device to protect the motor
- Full crank shaft
- Automatic voltage regulation
- Push bracket (9) and wheels (5) for easy transport



Technical Data

- Generator:
- Max. Power (S2 2 min):
- Nominal current:
- Frequency:
- Type:
- Cylinder capacity:
- Max. motor power:
- Fuel:
- Tank capacity:
- Running time at 2/3 load:
- Noise level:
- Product weight:

Logistic Data

Net weight:

- Gross weight:
- Packing dimensions:
- Bar code:
- Sales unit:

Synchronous 1 x 2,600 W 1 x 3,100 W 2 x 230 V 50 Hz 1 cylinder, 4-stroke air cooled 208 cm³ 4.1 kW / 5.6 HP Petrol 15 I approx. 11 hours 96 dB (A) 42.4 kg

42.5 kg 45.5 kg 625 x 465 x 475 mm 4006825 589368



Abbildungen können nicht im Serien-Lieferumfang enthaltenes Zubehör darstellen / Illustrations can contain accessories, which are not included in standard extent of delivery. Abbildungen ähnlich, produktionsbedingte Abweichung vorbehalten / Illustration similar (in design), production-wise modifications reserved. File: S:\shared-pool\Product-Documentation\T-Produktbeschreibung\30_n0t\Originale_Englisch_PA04\4152460_11012.doc Erstelldatum/create date: 07.02.2013 13:28:00Aktualisiert/up dated: 13.02.2013

Continuous Power (S1):