





BT-PG 2800/1

Power Generator (Petrol) Art.-Nr.: 4152480 Ident-Nr.: 11024

The powerful BT-PG 2800/1 petrol generator ensures that power is available reliably and permanently in remote places and during a mains power failure. Light sources and other electrical devices can be easily operated from two 230V socket outlets With a continuous output of 2300 W, the combination of synchronous generator and long-lasting four-stroke engine supplies plenty of power for a wide range of applications.

Features

- · Smooth-running and long-lasting 4-stroke engine
- Crank shaft mounted at two ends
- · Low oil cut-out to protect against engine damage
- Reversing starter
- Synchronous generator
- AVR function: Stable output power for electronically consumers
- 2 x 230 V socket
- Voltmeter
- Overload switch for appliance safety
- Large 15 liter tank with level indicator
- · Sturdy wheels, hinged handle and carry-frame for easy transport

Synchronous

2800 W | 2 min

four-stroke, air cooled

50 Hz 2300 W

10 A

2 Pieces

1 Pieces

208 cm³

4.1 kW

Petrol

15 L

13.6 h

96 dB (A)

3000 min^-1

· Sturdy feet



Technical Data

- Type of generator
- Frequency
- Continous power (S1) at 230 V
- Max. power (S2 | S2time) at 230 V
- Nominal current at 230 V
- 230 V socket
- Engine
- Number of cylinders
- Engine displacement
- Engine speed
- Max. engine power
- Fuel
- Capacity of fuel tank
- Running time with 2/3 load
- Sound power level LWA

Logistic Data

• Product weight41.75 kg• Gross weight single packaging44.55 kg• Dimensions single packaging620 x 410 x 475 mm• Pieces per export carton1 Pieces• Gross weight export carton44.55 kg• Dimensions export carton625 x 460 x 475 mm• Container quantity (20"/40"/40"HC)180 | 380 | 475

Illustrations can contain accessories, which are not included in standard extent of delivery Illustration similar (in design), production-wise modifications reserved GS mark belongs to the product itself only, excluded accessory









